Internal Layout

Back Panel

AVAILABLE ADD-ON MODULES

MOVING MAGNET

GAIN STAGE

HEADPHONE

- **Phono Module** adds a high quality Creek phono stage (MM or MC) for playback of conventional records.
- **Headphone Module** powers most headphones.
- **Supplemental Gain Stage Module** adds active output stages for independent adjustment of multi-room or bi/tri-amplification. Up to three can be used simultaneously.
- **Bridging Output Module** converts two standard Creek A42 power amps into mono-blocks and raises their output from 50 watts to 150 watts.

CREEK P42 PREAMPLIFIER TECHNICAL SPECIFICATIONS

Total Harmonic Distortion:	**<0.01% 20Hz to 20kHz**
Frequency Response:	**3Hz to 35kHz -1dB**
Line Inputs:	**x 4 at 47Ω**
Tape Loops:	**x 2**
Outputs:	**x 3 Maximum**
Tape Outputs:	**x 2 at 1kΩ**
Gain from Outputs 2&3 with LINK PCB:	**x 1 (0dB)**
Gain from Output 1 switchable:	**x 2 (6dB), x 3 (9dB), x 4 (12dB)**
Maximum Output Voltage per module:	**6V at 10kΩ load**
Output Impedance:	**1kΩ**
Signal to Noise Ratio:	**-105dB for 600mV output**
Separation:	**-80dB at 1kHz**
Power Consumption:	**7W DC (15W AC mains version)**
Power Requirements:	**+35 & -36V DC from A42**
Weight Packed:	**3.7 Kgs 9lbs.**
Size:	**420 x 60 x 230mm, 16.5" x 2.4" x 9"**

Creek
AUDIO LIMITED
2 Bellevue Road, Friern Barnet,
London N11 3E$, England
Tel: 081 361 4133
Fax: 081 361 4136

Creek Audio Limited reserves the right to modify or change the specifications of its products at any time without notice.